



GSS-A Calibration

-For 0-5V analog sensors, use sensor calibration voltage -

32 cells are calculated, for 16 or 8 cell input, use every other, or fourth cell as necessary

Liquid Sensors		Lo-AT Sensors		Hi-AT Sensors	
F°	V	F°	V	F°	V
-20	4.94	-20	4.62	-10	4.99
-10	4.92	-10	4.49	20	4.98
0	4.88	0	4.33	40	4.96
10	4.84	10	4.15	60	4.93
20	4.78	20	3.93	80	4.88
30	4.71	30	3.69	95	4.83
40	4.62	40	3.42	110	4.76
50	4.51	50	3.14	125	4.67
60	4.38	60	2.86	140	4.55
70	4.22	70	2.57	155	4.41
80	4.04	80	2.30	170	4.23
90	3.84	90	2.04	185	4.03
100	3.62	100	1.80	200	3.80
110	3.39	110	1.58	215	3.55
120	3.14	120	1.38	230	3.28
130	2.89	130	1.20	245	3.00
140	2.64	140	1.05	260	2.73
150	2.40	150	0.91	275	2.45
160	2.16	160	0.79	290	2.19
170	1.94	170	0.69	305	1.95
180	1.73	180	0.60	320	1.73
190	1.54	190	0.53	335	1.52
200	1.37	200	0.46	350	1.34
210	1.22	210	0.41	365	1.18
220	1.08	220	0.36	380	1.04
230	0.95	230	0.32	395	0.91
240	0.84	240	0.28	410	0.80
250	0.75	250	0.25	425	0.70
260	0.66	260	0.22	440	0.62
270	0.59	270	0.20	455	0.55
280	0.52	280	0.18	470	0.49
290	0.47	290	0.16	485	0.43